

SWIT®

4 × 6A CH SUPER FAST CHARGER

PC-P461A/S

Charge both 14.4V & 28.8V
V-mount Batteries



SAVE 60% CHARGING TIME



3.5-inch Color LCD Display

Ready for mounting battery

1 READY Please put on battery.	2 62% CURRENT 5.95A VOLTAGE 15.22V	Capacity percentage Progress bar Charging current Realtime voltage
3 E03 Battery over heat.	4 89% CAPACITY 17889mAh CYCLE 005	Realtime capacity* Battery cycle times* (*SMBUS Digital battery only)

Charging abnormal Warning
(Following on-screen instructions to take steps)



Charging time Compare

SWIT Over 160Wh batteries - **100W/6A Charging**
All Other batteries - **50W/3A Charging**

Battery Capacity	2A normal Charger	3A Fast Charger	PC-P461A/S 6A Super Fast
160Wh	6h20m	4h15m ↓	2h35m ↓↓
220Wh	8h30m	6h15m ↓	3h30m ↓↓
260Wh	9h55m	7h10m ↓	4h15m ↓↓
290Wh	10h30m	7h40m ↓	4h50m ↓↓

↓↓ Save up to 60% charging time comparing to normal charger



Specifications

Model	PC-P461A	PC-P461S
Type	Gold mount	V-mount
Input	100~240VA, 50/60Hz	
Power	450W (Max)	
Charging output	DC 16.8V, 6A×4 (SWIT 14.4V & ≥160Wh batteries) DC 33.6V, 3A×4 (SWIT 28.8V & ≥160Wh batteries)* DC 16.8V, 3A×4 (Other batteries)	
Dimensions	330×135.6×162mm	330×153×162mm
Net weight	Approx. 2.43kg	

* Gold Mount PC-P461A doesn't output DC33.6V to charge high voltage batteries.

SWIT Electronics Co., Ltd.
+86-25-85805753
<http://www.swit.cc>
Email: contact@swit.cc

SWIT Electronics America, Inc
1-(408)260-8258
<http://www.switusa.com>
Email: info@swit.us

SWIT Electronics Europe GmbH
+49(0)21316632331
<http://www.switeu.com>
Email: info@swit-europe.com



Facebook Page



Instagram