

# SWIT®



## 2-ch Simultaneous B-mount Charger

**S-3822B** [BIVO ONLY]

**B-MOUNT**  
CINE POWER SYSTEM



### 16.8V 3A×2-ch Charging

The S-3822B charges B-mount batteries at DC16.8V, compatible with the B-mount batteries that support 14.4V nominal voltage mode, like SWIT BIVO series, Bebob and CoreSWX Bi-voltage series.

[BIVO ONLY]



### DC 15V 6A 90W Output

The S-3822B has a 4-pin XLR female connector on the front panel, and you can use the charger as AC-DC adaptor of DC 15V, 6A, 90W output.

Please note the AC-DC adapting output will not work when battery is charging.



### Charging Time Chart

Battery Model	Capacity	Charging Speed	Fully Charging Time
BIVO-98	98Wh	16.8V 3A 50W	2h 45m
BIVO-160	160Wh	16.8V 3A 50W	4h
BIVO-200	196Wh	16.8V 3A 50W	5h 15m
BIVO-290	290Wh	16.8V 3A 50W	7h 15m



### Specifications

Model	S-3822B
Type	B-mount
Input	100~240VA, 50/60Hz
Power	136W (Max)
Charging output	DC 16.8V, 3A (50W)×2
Adapting output	4-pin XLR DC 15V 6A (90W) ×1
Dimensions	228×140×120mm
Net weight	Approx. 1.0kg

SWIT Electronics Co., Ltd.  
+86-25-85805753  
<http://www.swit.cc>  
Email: [contact@swit.cc](mailto:contact@swit.cc)

SWIT Electronics America, Inc  
1-(408)260-8258  
<http://www.switusa.com>  
Email: [info@swit.us](mailto:info@swit.us)

SWIT Electronics Europe GmbH  
+49(0)21316632331  
<http://www.switeu.com>  
Email: [info@swit-europe.com](mailto:info@swit-europe.com)



Facebook Page



Instagram